

BS ISO 12384:2010



BSI Standards Publication

Aerospace — Requirements for digital equipment for measurements of aircraft electrical power characteristics

NO COPYING WITHOUT BSI PERMISSION EXCEPT AS PERMITTED BY COPYRIGHT LAW

raising standards worldwide™

Copyright British Standards Institution
Provided by IHS under license with BSI - Uncontrolled Copy
No reproduction or networking permitted without license from IHS

Not for Resale



National foreword

This British Standard is the UK implementation of ISO 12384:2010.

The UK participation in its preparation was entrusted to Technical Committee ACE/6, Aerospace avionic electrical and fibre optic technology.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© BSI 2010

ISBN 978 0 580 66536 3

ICS 49.060

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 December 2010.

Amendments issued since publication

Date	Text affected
------	---------------

INTERNATIONAL STANDARD

BS ISO 12384:2010

ISO 12384

First edition
2010-11-15

Aerospace — Requirements for digital equipment for measurements of aircraft electrical power characteristics

Constructions aérospatiales — Exigences relatives aux équipements
numériques de mesure des caractéristiques de puissance électrique
à bord des aéronefs



Reference number
ISO 12384:2010(E)

© ISO 2010

PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.



COPYRIGHT PROTECTED DOCUMENT

© ISO 2010

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11 Fax + 41 22
749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Contents

Page

Foreword	iv
Introduction.....	v
1 Scope.....	1
2 Normative references.....	1
3 Terms and definitions.....	1
4 Symbols.....	1
5 Measurement requirements for the aircraft electric power characteristics.....	3
5.1 General rules, measurement states and the admissible errors of the measurement results.....	3
5.1.1 General	3
5.1.2 Measurement states.....	3
5.1.3 Admissible errors of the measurement results.....	3
5.2 Measurement of constant frequency (CF) a.c. power system characteristics.....	4
5.2.1 Steady state characteristics.....	4
5.2.2 Transient characteristics.....	8
5.3 Measurement of variable frequency (VF) a.c. power system characteristics.....	8
5.4 Measurement of d.c. power system characteristics (28 V or 42 V system).....	8
5.4.1 Steady state characteristics.....	8
5.4.2 Transient d.c. voltage.....	10
5.5 Measurement of current parameter.....	10
5.6 Measurement of power transfer characteristics	10
5.7 Measurement of voltage spike characteristics	10
5.8 Measurement of power factor	10
6 General requirements for the measuring equipment	11
6.1 Applicability	11
6.1.1 Efficiency.....	11
6.1.2 Operating environment.....	11
6.2 Performance and functions.....	11
6.2.1 Accuracy	11
6.2.2 Scope of the measuring equipment	11
6.2.3 Measurement resolution.....	11
6.2.4 Input impedance.....	11
6.2.5 Sampling frequency range	12
6.3 Electromagnetic compatibility	12
6.4 Human-machine interface project	12
6.5 The regulation of select measuring equipment	12
6.5.1 The measurement regulation of the data process software	12
6.5.2 Selecting requirement.....	12
Bibliography.....	13

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of technical committees is to prepare International Standards. Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the member bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights.

ISO 12384 was prepared by Technical Committee ISO/TC 20, Aircraft and space vehicles, Subcommittee SC 1, Aerospace electrical requirements.

ISO 12384 is closely allied with ISO 1540 and references from one to the other are freely used, particularly from ISO 12384 to ISO 1540. The proper use of this International Standard through referencing the applicable specific digital measurement methods should simplify the preparation of specifications and help to expedite the purchase and acceptance of the digital measuring equipment.

Introduction

Various types of digital measuring equipment for electrical power characteristics are applied to the aircraft electrical system. There is no International Standard for digital measuring equipment for electrical power characteristics in the aerospace industry. The purpose of this International Standard is to explain, establish and standardize specific methods for digital measurements of the aircraft electrical system. The intended use of this International Standard is to define how to measure parameters of electrical characteristics in aircraft electrical power systems. The specific measurement methods are included here, while the terminology and general methods of digital measurement and signal processing are also presented. The requirements of digital measuring equipment are verified by testing of the aircraft electrical system.



Aerospace — Requirements for digital equipment for measurements of aircraft electrical power characteristics

1 Scope

This International Standard specifies the requirements for digital measuring methods and digital measuring equipment for aircraft electrical power characteristics, including accuracy, algorithms and digital measuring equipment. The measuring equipment should be applied mainly for the use of laboratory or rig tests.

This International Standard can be applied to digital measuring equipment which is involved in the measurement of power electrical characteristics of the power supply system, power distributing systems and the utilization of equipment in aircrafts.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 1540, Aerospace — Characteristics of aircraft electrical systems

ISO 7137, Aircraft — Environmental conditions and test procedures for airborne equipment

3 Terms and definitions

For the purposes of this document, the terms and definitions given in ISO 1540 and the following apply.

3.1

sampling frequency
reciprocal of sampling interval time

3.2

sampling time
total of sampling interval time

4 Symbols

Symbols used by this International Standard are listed in Table 1.

5 Measurement requirements for the aircraft electric power characteristics

5.1 General rules, measurement states and the admissible errors of the measurement results

5.1.1 General

The electric power characteristics measurement shall be implemented in accordance with the definitions of ISO 1540 and the requirements of this International Standard.

5.1.2 Measurement states

5.1.2.1 Steady state

The measurement of steady state parameters shall be processed only when negligible changes in electrical parameters appear. For example, no load state, rated load state, etc.

5.1.2.2 Transient state

The measurement of transient state parameters shall be processed in the transient state. Momentary variations of a characteristic from its steady state limits, and back to its steady state limits may occur as a result of a system disturbance. For example, apply the load immediately, switch from one load to another load, power bus or power source switching, building up and shut down power source, etc. The whole transient procedure should be tested.

5.1.3 Admissible errors of the measurement results

5.1.3.1 Steady state characteristics

When measuring voltages and currents within the range of waveform characteristics allowed in ISO 1540, the steady state measurement error shall meet the following requirements:

a) voltage:

- 1) steady state a.c. and d.c. voltage: in the range of measurement, the absolute error of readings shall be in the range of $\pm 0,5$ %;
- 2) D.C. component of the a.c. voltage: the absolute error of readings shall be in the range of ± 10 %;

b) current:

- 1) steady state a.c. current: in the range of measurement, the absolute error of readings shall be in the range of ± 1 %;
- 2) steady state d.c. current: in the range of measurement, the absolute error of readings shall be in the range of $\pm 0,8$ %;

c) frequency:

the a.c. system: in the range of measurement, the absolute error of readings shall be in the range of $\pm 0,1$ % of the nominal frequency;

d) phase difference:

in the condition that the voltage phase difference is in the range of $110^\circ \sim 130^\circ$, the absolute error of readings shall be in the range between $\pm 0,2^\circ$;

e) amplitude of distortion spectrum:

the absolute error shall be in the range between $\pm 5\%$ of limited value.

5.1.3.2 Transient characteristics

Measurement error of the transient characteristics should meet the following requirements:

a) voltage:

- 1) a.c. voltage: in the range of measurement, the absolute error of readings shall be in the range of $\pm 1,0\%$ of the specified maximum transient a.c. voltage;
- 2) d.c. voltage: in the range of measurement, the absolute error of readings shall be in the range of $\pm 1,0\%$ of the specified maximum transient d.c. voltage;
- 3) d.c. content of the a.c. voltage: absolute error of readings shall be in the range of $\pm 10\%$ of the specified maximum transient d.c content voltage;

b) current:

- 1) a.c. current: in the range of measurement, the absolute error of readings shall be in the range of $\pm 2\%$ of the specified maximum transient a.c. current;
- 2) d.c. current: in the range of measurement, the absolute error of readings shall be in the range of $\pm 2\%$ of the specified maximum transient d.c. current;

c) frequency:

in the range of measurement, the absolute error of readings shall be in the range of $\pm 0,2\%$ of the specified maximum frequency.

5.2 Measurement of constant frequency (CF) a.c. power system characteristics

5.2.1 Steady state characteristics

5.2.1.1 Phase voltage

The measurement of the phase voltage should be processed according to the following:

- a) sampling frequency on each phase voltage not less than 72 kHz;
- b) the three phase voltages sampled at the same time;
- c) sampling time over a period not to exceed one second.

Calculate the steady state phase voltage according to Equation (1):

$$U = \sqrt{\frac{1}{T_w} \sum_{j=1}^n u_j^2 \Delta t} \quad (1)$$

where

U is steady state phase voltage, V;

T_w is the time of a period not to exceed one second, s;

- n is the number of samples;
 j is sample serial, $j = 1, 2, 3 \dots n$;
 u_j is the instantaneous value of a.c. voltage, V;
 Δt is the sampling interval time, s.

5.2.1.2 Phase voltage imbalance

The measurement of the voltage imbalance should be processed according to the following requirements:

- calculate the steady state a.c. voltage U_A, U_B, U_C according to 5.2.1.1;
- substitute the U_A, U_B, U_C into Equation (2) to calculate the phase voltage imbalance.

$$U_{\varepsilon} = \max \left[\left| \begin{array}{ccc} U_A & -U_B & U_C \\ U_B & -U_C & U_A \\ U_C & -U_A & U_B \end{array} \right| \right] \quad (2)$$

where

U_{ε} is phase voltage imbalance, V.

5.2.1.3 Phase voltage modulation

Each phase voltage should be sampled at the frequency of more than 72 kHz. The sampling time should be at least one second. Calculate the positive peak voltage of each phase in every cycle, denoted as $U_{PAj}, U_{PBj}, U_{PCj}$ ($j = 1, 2, 3, \dots, n$) and find out the maximum value and minimum value from these series:

$$U_{PAj,max}; U_{PAj,min}; U_{PBj,max}; U_{PBj,min}; U_{PCj,max}; U_{PCj,min}$$

Substitute them into Equation (3) to calculate the phase voltage modulation:

$$U_m = \max \left[\left| \begin{array}{ccc} U_{PAj,max} & -U_{PBj,max} & U_{PCj,max} \\ U_{PBj,max} & -U_{PCj,max} & U_{PAj,max} \\ U_{PCj,max} & -U_{PAj,max} & U_{PBj,max} \end{array} \right| \right] \quad (3)$$

where

U_m is voltage modulation, V.

According to the positive peak voltage of every cycle in each phase, the cyclic or random variation of a.c. peak voltage can be obtained by computing the amplitude of the components at individual frequencies by the Fourier transformation, then plotting the frequency characteristics of voltage modulation.

5.2.1.4 Phase voltage displacement

Each phase voltage shall be sampled at the same time. The sampling time should be over a period not to exceed one second. The difference period among the three phases should not be more than one cycle of a fundamental component, finding the positive zero-crossing of the fundamental component wave of each phase and the period between the consecutive positive zero-crossing. Calculate the angle between the fundamental components of the two phase voltage according to Equation (4) which is the phase voltage displacement.

$$\theta = \frac{t}{T} \cdot 360^\circ \quad (4)$$

where

θ is the phase voltage displacement (electrical angle difference between the two fundamental component waves), (the unit is electrical angle);

t_θ is the period between the two consecutive positive zero-crossings of the fundamental component wave, s;

T_θ is the period between the consecutive positive zero-crossing of the normalized phase voltage fundamental component wave (cycle), s.

Measure the phase difference of fundamental components of any two phase voltages.

5.2.1.5 A.C. voltage distortion factor

Sample the distorting a.c. voltage with proper sampling frequency. The sampling time should be over a one second period. Calculate the a.c. voltage U according to Equation (1) and U_f . Then the a.c. voltage distortion factor can be obtained by using Equation (5).

$$F_d (\%) = 100 \times \frac{\sqrt{U^2 - U_f^2}}{U_f} \quad (5)$$

where

F_d is the a.c. voltage distortion factor;

U is the steady state phase voltage, V;

U_f is the rms value of fundamental component, V.

5.2.1.6 Total harmonic distortion (current or voltage)

Sample the a.c. voltage or current waveform at a frequency of more than 200 KHz. The sampling time should be over a period of one second. Calculate the rms of fundamental component, and the n^{th} harmonic component of current or voltage. Then the total harmonic distortion can be obtained by using Equation (6).

$$D_{TH} (\%) = 100 \times \frac{\sqrt{\sum_{n=2}^n U_n^2}}{U_f} \quad (6)$$

where

U_f is the rms value of fundamental component of current or voltage;

U_n is the rms value of n^{th} harmonic component of current or voltage.

5.2.1.7 A.C. voltage distortion spectrum

Sample the distortion a.c. voltage with proper sampling frequency. The sampling time should be over a period of one second (which is the period of testing steady state voltage T_w); calculate the rms value of each

frequency component, and plot the spectrum curve.

6

Copyright British Standards Institution
Provided by IHS under license with BSI - Uncontrolled Copy
No reproduction or networking permitted without license from IHS

© ISO 2010 – All rights reserved

Not for Resale

5.2.1.8 Crest factor

Each phase voltage should be sampled at a frequency of more than 72 kHz. The sampling time should be over a one second period. Calculate the rms value of each cycle U_j ($j = 1, 2, 3, \dots, n$) during the sampling time, getting the peak value of each cycle U_{pj} ($j = 1, 2, 3, \dots, n$) and calculate the crest factor F_C of each cycle using Equation (7). Then find the extreme value from a series of F_C .

$$F_C = \frac{|U_{pj}|}{U_j} \quad (7)$$

where

F_C is the crest factor;

U_{pj} is the voltage peak value corresponding to the j^{th} cycle, V;

U_j is the rms value corresponding to the j^{th} cycle, V.

5.2.1.9 D.C. component of the a.c. voltage

After a.c. components have been filtered out, phase voltage should be sampled at the frequency of more than 72 kHz. The sampling time should be over a period not to exceed one second. Then calculate the d.c. component of the phase voltage according to Equation (8).

$$U_{\text{Adc}} = \frac{\sum_{j=1}^n u_j}{n} \quad (8)$$

where

U_{Adc} is the d.c. component of the a.c. voltage, V;

u_j is the instantaneous value of a.c. phase voltage, V;

j is the sampling serial, $j = 1, 2, 3, \dots, n$;

n is the total number of sampling points during the steady state time.

5.2.1.10 Steady state frequency

The sampling time should be over a period not to exceed one second. Calculate steady state frequency according to Equation (9).

$$f = \frac{N}{T_w} \quad (9)$$

where

f is steady state frequency, Hz;

n is the cycle numbers during T_w .



5.2.1.11 Frequency modulation

Sample the phase voltage at a frequency of more than 72 kHz, compute the frequency of each cycle, and get the maximum frequency f_{\max} and minimum frequency f_{\min} in one minute, then calculate the frequency modulation.

$$f_m = f_{\max} - f_{\min} \quad (10)$$

where f_m is the frequency modulation, Hz.

According to the frequency of each cycle in one second, the frequency modulation amplitude can be obtained in different repetition rates. Plot the frequency modulation curve.

5.2.2 Transient characteristics

5.2.2.1 Voltage transients

Sample the transient wave of a.c. voltage at a frequency of more than 100 kHz. The sampling time should be more than 0,25 s. Calculate the RMS of each cycle by using Equation (1), and then plot normal transient voltage envelope.

Sample the transient voltage of over-load, under-load a.c. voltage at a frequency of more than 100 kHz. The sampling time should be more than 10 s. Calculate the RMS of each cycle by using Equation (1), and then plot abnormal transient voltage envelope.

5.2.2.2 D.C. content transients

Sample the transient wave of a.c. voltage at a frequency of more than 100 kHz. The sampling time should be more than 10 s. Calculate the average value of each cycle by using Equation (8), and then plot abnormal d.c. content transient envelope.

5.2.2.3 Transient frequency

Sample the normal a.c. frequency or over-frequency, under-frequency transient wave at a frequency of more than 100 kHz. The sampling time should not be less than 10 s. Calculate the frequency of each cycle, and then plot the normal a.c. frequency or over frequency, under-frequency transient envelope.

5.3 Measurement of variable frequency (VF) a.c. power system characteristics

The characteristics of the VF system should be measured according to the items in 5.2, but the sampling frequency should be increased according to the ratio of the VF system's high frequency to CF system's rating frequency.

5.4 Measurement of d.c. power system characteristics (28 V or 42 V system)

5.4.1 Steady state characteristics

5.4.1.1 Steady state d.c. voltage

Sample the instantaneous value of d.c. voltage at a frequency of more than 20 KHz. The sampling time should be over a one second period, calculating the steady state d.c. voltage using Equation (11).

$$U_{dc} = \frac{1}{n} \sum_{j=1}^n u_{dcj} \quad (11)$$

where

- U_{dc} is steady state d.c. voltage, V;
- u_{dcj} is the instantaneous value of d.c. voltage, V;
- j is the sampling serial, $j = 1, 2, 3, \dots, n$;
- n is the total number of sampling points.

5.4.1.2 D.C. distortion factor

Sample the ripple of the d.c. voltage at a frequency of more than 20 KHz. The sampling time should be near or equal to one second. Calculate the d.c. voltage distortion by using Equation (12):

$$U_{Ddc} = \sqrt{\frac{1}{T} \sum_{j=1}^n u_{Dj}^2 \Delta t} \quad (12)$$

where

- U_{Ddc} is the distortion of the d.c. voltage, V;
- T is the sampling period (near or equal to 1s), s;
- u_{Dj} is the instantaneous value of the a.c. voltage distortion wave, V;
- j is the sampling serial, $j = 1, 2, 3, \dots, n$;
- n is the total number of sampling points;
- Δt is the sample interval time points, s.

By submitting the d.c. voltage distortion derived from Equation (12) and steady state d.c. voltage into Equation (13), the d.c. voltage distortion factor can be obtained.

$$F_{ddc} (\%) = 100 \times \frac{U_{Ddc}}{U_{dc}} \quad (13)$$

where

- F_{ddc} is the d.c. voltage distortion coefficient;
- U_{Ddc} is the d.c. voltage distortion, derived from Equation (13), V;
- U_{dc} is the steady state d.c. voltage, V.

5.4.1.3 D.C. voltage distortion spectrum

According to 5.4.1.2, sampling the a.c. components of d.c. voltage wave and the sampling time should be less than one second. Individual frequency components of ripple are obtained by calculating the rms of each frequency component through the Fourier transformation. Then plot the spectrum curve.

5.4.1.4 D.C. voltage ripple

Sample the d.c. voltage at a frequency of more than 20 kHz (eliminate the voltage spike and filter out the abnormal disturbance). The sampling time should be near or equal to one second. Find the maximum u_{dmax} and the minimum u_{dmin} from instantaneous cycle voltage. Calculate the d.c. voltage by using Equation (14):

$$U_{rm} = \frac{u_{dmax} - u_{dmin}}{2} \quad (14)$$

where U_{rm} is the d.c. voltage ripple, V.

5.4.2 Transient d.c. voltage

Sample d.c. voltage waveform at a frequency of more than 80 kHz. The sampling time should not be less than 0,25 s. Measure the instantaneous value of d.c. voltage. Plot the normal transient d.c. voltage envelope.

Sample d.c. voltage waveform at a frequency of more than 80 kHz. The sampling time should not be less than 10 s. Measure the instantaneous value of d.c. voltage. Plot the over-voltage and under-voltage abnormal transient envelope.

5.5 Measurement of current parameter

The measurement method and data processing principle of the CF system can use the corresponding measurement method of the voltage. The sampling frequency should not be less than 20 kHz. However, the sampling frequency should be increased when measuring the transient current, and when measuring the distortion of the current, the sampling frequency should be increased further.

The measurement method and data processing principle of the variant frequency a.c. system can be referred to the corresponding methods of the CF a.c. system. However, the sampling frequency should be increased according to 5.3.

5.6 Measurement of power transfer characteristics

Measure the period of the voltage and frequency between the zero and normal working limit when switching between power bus and power source. Inspect the waveform of the testing point according to the transient measurement method of the voltage and frequency. Calculate the transfer period between the waveforms.

5.7 Measurement of voltage spike characteristics

Test the utilization equipment according to the testing equipment and method regulated in ISO 7137. Determine the testing result according to the regulations in ISO 1540.

5.8 Measurement of power factor

Sample the a.c. voltage and current waveform at the same time. The sampling frequency should not be less than 72 kHz. The sampling time should be a period not exceeding one second. Calculate the steady state a.c. voltage U which has been stated in 5.2.1.2. Calculate the a.c. current I stated in 5.5, and calculate the power factor according to Equation (15).

$$F_P = \frac{1}{n} \frac{\sum_{j=1}^n u_j i_j \Delta t}{U_w I} \quad (15)$$

where

F_P is the power factor when voltage and current distortion, θ doesn't equals to the difference angle of the u, i waveform;

U is the steady state a.c. voltage (calculated according to 5.2.1.1), V;

I is the steady state a.c. current (calculated according to 5.5), A;

T_w is a period not to exceed one second, s;

j is the sample serial, $j = 1, 2, 3, \dots n$;

u_j is the instantaneous value of a.c. voltage, V;

i_j is the instantaneous value of a.c. current, A;

Δt is the sampling interval time, s.

6 General requirements for the measuring equipment

6.1 Applicability

6.1.1 Efficiency

The measuring equipment shall be able to measure the characteristics of power supply according to Clause 5. The results shall be in accordance with the definition stated in ISO 1540.

6.1.2 Operating environment

The measuring equipment shall be able to work under the regulated environment (e.g. inner field, outfield, in the vehicle and airborne). The additional error shall not cause the measurement result to exceed the admissible errors stated in 5.1.3 when the environmental factors vary in the range of the regulated conditions.

6.2 Performance and functions

6.2.1 Accuracy

The accuracy of the measuring equipment shall comply with the requirements in 5.1.3.

6.2.2 Scope of the measuring equipment

The scope of the measuring equipment shall comply with the range of transient characteristic parameters stated in ISO 1540.

6.2.3 Measurement resolution

The measuring equipment shall be able to detect the 0,05 % variation of the maximum limited value stated in ISO 1540.

6.2.4 Input impedance

The variation of influence to the measured system caused by the measuring equipment input variation shall not exceed the range of limit in resolution of the measuring equipment.

6.2.5 Sampling frequency range

According to the characteristics of the measured system, the sampling frequency should not be lower than 200 kHz (when measuring a.c. or d.c. voltage distortion factor and a.c. or d.c. voltage distortion spectrum); 100 kHz (measuring the a.c. transient characteristics); 80 kHz (measuring the d.c. transient characteristics); 72 kHz (measuring other characteristics of the a.c.); 20 kHz (when measuring d.c. voltage, the d.c. voltage ripple range and steady state current).

6.3 Electromagnetic compatibility

The measuring equipment should not produce electromagnetic disturbance to the equipment under test and the measuring equipment shall work well as long as the electromagnetic disturbance of the tested system does not exceed the regulation limit.

6.4 Human-machine interface project

Operation of the measurement system should be simple. Human-machine interface should be user-friendly. The operation mistake should not be able to cause damage to the measurements or measured system.

6.5 The regulation of select measuring equipment

6.5.1 The measurement regulation of the data process software

The data processing method of the measuring equipment software shall comply with the definition of the corresponding power supply characteristics stated in ISO 1540 and fulfill the regulation requirements in this International Standard.

6.5.2 Selecting requirement

The measuring equipment which has been calibrated and warranted by the calibrating and testing department of the country should be selected.

Bibliography

- [1] ISO 6858, Aircraft — Ground support electrical supplies — General requirements

ICS 49.060

Price based on 13 pages

British Standards Institution (BSI)

BSI is the independent national body responsible for preparing British Standards and other standards-related publications, information and services.

It presents the UK view on standards in Europe and at the international level.

It is incorporated by Royal Charter.

Revisions

British Standards are updated by amendment or revision. Users of British Standards should make sure that they possess the latest amendments or editions.

It is the constant aim of BSI to improve the quality of our products and services. We would be grateful if anyone finding an inaccuracy or ambiguity while using this British Standard would inform the Secretary of the technical committee responsible, the identity of which can be found on the inside front cover.

Tel: +44 (0)20 8996 9001 Fax: +44 (0)20 8996 7001

BSI offers Members an individual updating service called PLUS which ensures that subscribers automatically receive the latest editions of standards.

Tel: +44 (0)20 8996 7669 Fax: +44 (0)20 8996 7001
Email: plus@bsigroup.com

Buying standards

You may buy PDF and hard copy versions of standards directly using a credit card from the BSI Shop on the website www.bsigroup.com/shop. In addition all orders for BSI, international and foreign standards publications can be addressed to BSI Customer Services.

Tel: +44 (0)20 8996 9001 Fax: +44 (0)20 8996 7001
Email: orders@bsigroup.com

In response to orders for international standards, it is BSI policy to supply the BSI implementation of those that have been published as British Standards, unless otherwise requested.

Information on standards

BSI provides a wide range of information on national, European and international standards through its Knowledge Centre.
Tel: +44 (0)20 8996 7004 Fax: +44 (0)20 8996 7005
Email: knowledgecentre@bsigroup.com

Various BSI electronic information services are also available which give details on all its products and services.

Tel: +44 (0)20 8996 7111 Fax: +44 (0)20 8996 7048
Email: info@bsigroup.com

BSI Subscribing Members are kept up to date with standards developments and receive substantial discounts on the purchase price of standards. For details of these and other benefits contact Membership Administration.

Tel: +44 (0)20 8996 7002 Fax: +44 (0)20 8996 7001
Email: membership@bsigroup.com

Information regarding online access to British Standards via British Standards Online can be found at www.bsigroup.com/BSOL

Further information about BSI is available on the BSI website at www.bsigroup.com/standards

Copyright

Copyright subsists in all BSI publications. BSI also holds the copyright, in the UK, of the publications of the international standardization bodies. Ex-

cept as permitted under the Copyright, Designs and Patents Act 1988 no extract may be reproduced, stored in a retrieval system or transmitted in any form or by any means – electronic, photocopying, recording or otherwise – without prior written permission from BSI. This does not preclude the free use, in the course of implementing the standard of necessary details such as

symbols, and size, type or grade designations. If these details are to be used

for any other purpose than implementation then the prior written permission

of BSI must be obtained. Details and advice can be obtained from the Copyright & Licensing Manager.

Tel: +44 (0)20 8996 7070
Email: copyright@bsigroup.com

BSI Group Headquarters

389 Chiswick High Road London W4 4AL UK

Tel +44 (0)20 8996 9001
Fax +44 (0)20 8996 7001
www.bsigroup.com/standards



raising standards worldwide™

Copyright British Standards Institution
Provided by IHS under license with BSI - Uncontrolled Copy
No reproduction or networking permitted without license from IHS

Not for Resale